

Assembly Instructions


⚠ Important ⚠

Before you begin, read and comply with all safety and operating instructions, and ensure all parts and correct quantities are included.

Any parts damaged during shipment must be reported within 5 days of receipt. To report information regarding missing parts or damage, to purchase parts or accessories, or if you have any questions, please contact us.

www.spectrumfurniture.com
800-235-1262, 715-723-6750

Thank you for purchasing Spectrum products!



(2) 0119430
Top / Bottom Panel




(2) 0119438
1"W x 15.5"L Polyethylene
slide with (S1101) 3/4"
double-sided tape



(16) 0100167
8-32 x 1/2" PH
thread-cutting screw



(4) 052436
Rack rail (21")



12RU Rack Cube 55228

Tools Required




Drill with
Phillips
driver



Phillips
Screwdriver

1. Assemble Cube

1. Assemble the cube top, bottom, and four rack rails using (16) 8-32 x 1/2" PH thread-cutting screws. Note the orientation of the rails. **Figure 1.**
2. Tighten screws securely.



8-32 x 1/2" PH
thread-cutting screw
(16 required)

Figure 1

2. Apply Slides

1. Apply the polyethylene slides to the bottom panel as shown. **Figure 2.**




Figure 2

3. Install Rack Cube

1. Open door to provide better access. **Figure 3.**
2. Place the cube assembly into the unit.

The rack cube provides 12RU of rack space and is easily removed from the unit. This simplifies installation of equipment and provides the ability to integrate equipment remotely. The cube can also be installed into the unit at a later date or when convenient.

The cube also provides mounting capabilities for multiple cooling fans if necessary. Compatible with most 4.75" cooling fans with 4.13" mounting hole spacing (12 mounting locations available).




Figure 3